



**SMOKE**  
SMART SENSOR SERIES  
#SmartSense

Works Well With:  
 Google Assistant  
 amazon alexa

**DESCRIPTION**

The Smoke Sensor enables you to detect any accidental fire breakout in your home and triggers an alarm IN TIME to help you to take the necessary precautions for your family & safely douse the fire.

LED SIGNAL	SOUND	WHAT IT MEANS
<b>RED LED ON</b>	Buzzer Sound	Fire Alarm
<b>RED GREEN &amp; YELLOW LED flashing alternately</b>	No Sound	Smoke Sensor Warming Up
<b>GREEN LED ON</b>	No Sound	Normal Working mode
<b>YELLOW LED ON</b>	Buzzer Sound	False Alarm



FIRE ALERT



ZIGBEE COMPATABILITY



EASY INSTALLATION



LINKAGE TO OTHER SMART DEVICES



APP CONTROL



VOICE CONTROL


**SPECIFICATIONS**

Model No.	HSE-SM-001
Transmit Power	<-10dBm
Work Voltage	DC 3V (CR123A)
Standby/Working Current	<= 9 µA / <= 50 µA
Dimensions	70 x 70 x 29 mm
Operating Temperature	-10° C - +55 °C
Humidity	0 - 95%, No Condensation
Wireless Protocol	ZigBee 3.0
Alarm Sound	> 85 DB (@ 1m)
Detction Range	50 m²

**INSTALLATION**

Smoke Sensor can be installed on your ceiling either by screwing it on or by using a 3M tape. Screw Installation is **ALWAYS** preferred.

**SCREW MOUNTING**



**3M GLUE**

**ADDING SMOKE SENSOR TO YOUR HOME**

- Open the Hogar SE App and go to "Rooms".
- Click on "+" Button and select "Smoke Sensor". Follow the prompts on your App for subsequent operations.
- To turn on the Power Source, open the front cover of your Smoke Sensor by turning it **COUNTERCLOCKWISE** & remove the battery insulation strip.
- To **POWER ON** the Smoke Sensor, **Press and Hold** the button for 5 seconds.
- You will soon see the **GREEN LED** flash that indicates that the Smoke Sensor has entered into **Enrolling**.
- Click on "**Confirm Indicator Rapidly Blink**" on your Hogar SE App.

If the indicator is blinking fast, please skip the reset steps  
 ① Turn on the device  
 ② Hold RESET button (switch) for 5s. (please refer to the manual)  
 ③ Confirm that the indicator is blinking fast  
 Attention: please complete pairing process within 3 minutes after device reset.



Confirm indicator rapidly blink

- Your Smoke Sensor is now successfully added to your Hogar SE App.

**WARRANTY**

Hogar Provides Limited Warranty of 18 months on every product.

**ENQUIRY**

For Orders/Details, kindly reach out to us at [info@hogarcontrols.com](mailto:info@hogarcontrols.com)



Scan QR code for more details on warranty and sales enquiries